

## A757 GPRS AMR

The A757 GPRS AMR has been designed to meet the needs of applications such as remote meter reading and rainfall monitoring.

The A757 is fitted with a single pulse input which can be used in two modes: pulse count or event recording, the latter making it ideal for rain intensity monitoring.

The A757 is housed in a robust aluminum case. Sensor and power connections are made using waterproof Binder connectors.

Power comes from an internal NiMH battery which is charged using a compact solar panel. A single use Lithium-Thionyl battery is also available.

### Applications

- Remote Meter Reading
- Rain intensity monitoring networks
- Flood warning networks



### Technical data

Dimensions	6.46 x 2.36 x 3.15 in.	Operating time (without charging of internal battery)	in standard mode up to 21 days, in power-save mode up to 6 months; depends on transmission rate
Weight	2.52 lb.	Frequency range	850 / 900 / 1800 / 1900 MHz
Ingress Protection class	IP-67	Rx Sensitivity	-106 dBm
Temperature range	-22°F to +149°F	Tx Output Power	max. 2 W (depends on frequency)
Case	powder-coated aluminum	Transmission distance	max. 36km as per GSM standard
Screw connections	flange sockets of nickel-plated brass, stainless cover screws	Mounting	integrated mast-mounting bracket
Connectors (all connectors IP67 if properly mated or capped)	1x Binder M9 7-pin to Pulse counter 1x Binder M9 5-pin to solar cell / power supply 1x TNC Antenna connector	Antenna	omnidirectional quad-band, 2dBi
Power supply	6.2 V NiMH battery 3.1Ah + solar panel / mains adapter	Type approvals	FCC Part 15, Industry Canada, R&TTE, ACMA Australia, etc.
I/O Port	Pulse counter (normally open)	Ordering Information:	
Slot times	user specific (from 10sec. to 12h)	100.757.010	A757 GPRS AMR
Rain intensity feature	time-stamps each pulse	200.733.522	Solar Panel, 460mA
Internal memory	2MB for up to 500.000 values	900.000.187 / 188	Cable to Pulse output, 5m / 15m
		900.000.200 / 201	Cable to Pulse output, 10m / 20m
		900.000.567	ext. GSM antenna for mast mounting